

赤度 · 竟世界

深圳市赤度科技有限公司
地址: 深圳市光明区公明街道公明社区长春中道98号
电话: 0755-33922600
网址: CIDOO.COM

版权及声明: CIDOO 赤度 和其他赤度商标均为赤度公司所有。
开盒已即请注册, 所有其它商标均是其各自所有者的财产。

Shenzhen Cidoo Technology Co.,Ltd.
Add: 10A, Building 26, Changshun Garden, Guangming District, Shenzhen City, Guangdong Province, China



Copyrights and statements: CIDOO 赤度 and other cidoo trademarks are owned by Cidoo company and may have applied for registration.

Table with 5 columns: Part Name, Material, Price, Quantity, Quantity. Lists hazardous substances like Lead, Mercury, Cadmium, etc.

本产品所含有的有害物质都是由目前的科学技术而找不到替代的物质导致的。符合中国《电器电子产品有害物质限制使用管理办法》的要求。

保修卡
在购买产品时, 请完整清楚地填写下列信息, 并加盖公章, 以保障您的合法权益。

Table for warranty card with columns: User Information, Product Information, Sales Information, Contact Information.

欢迎选购赤度 V87 机械键盘, 希望您使用愉快, 功能操作说明请参考以下内容。

灯光设置按键
FN + 1: 背光灯效亮度增加
FN + -: 背光灯效亮度减小

多媒体按键
FN + A: Windows 系统 FN + S: Mac 系统
FN + F1: 音乐播放器 FN + F2: 音量减

2. 在要连接的设备上打开蓝牙, 搜索并选择其中一组 FN + Q 对应设备名 CIDOO V87-1, FN + W 对应设备名 CIDOO V87-2, FN + E 对应设备名 CIDOO V87-3.

关闭键盘电源开关蓝牙断开, 重新打开电源开关, CIDOO V87 会默认回到蓝牙重新打开所使用的设备

2.4G 模式使用方法:
请将键盘左上角三段拨动开关打开至左边靠近 USB 接口位置, 此时 R 键会闪烁绿色, 并将接收器插入电脑 USB 接口中, 此时 R 键停止闪烁, 背光灯亮起, 则表示 2.4G 设备已连接成功。


2.4G 对码方法:
键盘出厂默认已经完成 2.4G 对码, 如果需要重新配对, 可按如下方法重新对码。

自动休眠模式:
蓝牙和 2.4G 模式时, 键盘无按键操作 5 分钟后背光关闭, 按任意按键唤醒键盘

充电指示灯:
当键盘的电池电量低时(电池电量小于 3.5V), FN 键会持续闪烁红灯, 充电时 FN 键会常亮红灯。

自定义设置:
赤度 V87 支持 VIA 程序改键布局


1. 请访问 https://github.com/WestBerryVIA/via-releases/releases 选择您需要的最新的 VIA 软件然后下载并安装在电脑上, 如下图



2. 从赤度官网下载 CIDOO V87-2.4G.JSON 或 CIDOO V87-USB.JSON 文件并上传到 VIA 软件, 网址为: WWW.CIDOO.COM



3. 如下画面表示 VIA 软件安装完成并成功连接。



如果 VIA 软件无法识别您的键盘, 请联系我们的客服人员寻求帮助
如果您的键盘在哪里插入 VIA 会自动检测您的键盘是否兼容, 键盘记忆是持久的, 这意味着无论您在哪儿插入键盘, 它都会记住设置。

在 VIA 软件页面上半部分, 鼠标点击选择你想要更改的按键, 然后再用鼠标点击 VIA 软件页面下半部分中你想要更改的按键, 该按键功能生效。


宏设置:
CIDOO V87 按键中没有设置多媒体按键, 在此可以通过 VIA 软件映射多媒体按键到你想要的按键上。

特殊设置:
在此可以通过按键变更功能将特殊按键替换到你想要的按键上, 实现该功能的快速操作。

其他自定义:
CIDOO V87 VIA 软件中默认提供了多种不同的 RGB 灯光效果, 你可以在上面改变灯光亮度, 速度, 颜色以及定制你自己想要的灯光效果, 也可以更改按键来适应你所定制的对光效果。

CIDOO V87 提供其他功能按键的定制化改键


层 0: 当你使用键盘连接到 Win/Mac 系统设备时, 层 0 将被激活使用
层 1: 当你使用键盘连接到 Mac 系统设备时, 层 1 将被激活使用



层 1: 当你使用键盘连接到 Win/Mac 系统设备时, 长按 Fn1(3) 按键层 1 将被激活使用



层 2: 当你使用键盘连接到 Win/Mac 系统设备时, 通过 VIA 改键设置任意按键为 MO(2) 保存后, 长按 MO(2) 按键层 2 将被激活使用




层 3: 当你使用键盘连接到 Win/Mac 系统设备时, 通过 VIA 改键设置任意按键为 MO(3) 保存后, 长按 MO(3) 按键层 3 将被激活使用



按键说明

Table mapping keyboard keys to functions like Hue+, Sat+, RGB M+, RGB Tog., Win..., Mac..., Hue-, Sat-, BT 1, BT 2, BT 3, MO(3).



Cidoo VIA Tri-mode Aluminum Mechanical Keyboard
A Customizable Keyboard that Supports VIA Software

Thank you for purchasing our V87 mechanical keyboard... Default Hot Keys: Hold FN + listed keys to activate... LED Setting Keys: FN + : LED backlight brightness increase... Media Keys: FN + A: Windows System, FN + F1: Music Player, FN + F3: Volume +...

FN-WIN: Lock/Unlock Win FN-DEL: INSERT
USB Wired/BT5.0/2.4G Tri Mode Pairing Method:
Wired Mode: Please toggle the mode switch to wired mode... Bluetooth® Pairing Instructions: Perform the following steps to pair this keyboard with your device(s)...

The Bluetooth connection has memory. It will disconnect when power off the keyboard, and the keyboard will re-connect to the last device when power on the keyboard again.
2.4G mode Usage method:
1. Please toggle the mode switch to 2.4G mode. From left to right are 2.4Ghz -> Wired -> BT. "R" key will flashes green.
2. Plug the receiver into USB port of the device...

Battery Charging Indicator:
When the battery power of the keyboard is low (the battery power is less than 3.5V), the FN key will keep flashing red.
Custom Configuration:
CIDOO V87 supports using the VIA program to change key layout.
1. Please visit https://github.com/WestBerryVIA/via-releases/releases to download the latest VIA application for your computer's OS here.

3. The VIA software is installed and connected successfully if it is show as below photo.
If VIA software does not recognize your keyboard, please contact our customer service staff for assistance
VIA will automatically detect your keyboard compatibility if it's plugged in.

On the top half of VIA software, choose one key which you want to change by your mouse, and then select the key on the bottom half of VIA software, and it was effected.
See below for more information about configuration Macros setting
Macro Settings:
CIDOO V87 does not have physical multimedia keys, you can remap the keys through the VIA software to achieve the function.

Layer0: This layer will be activated when your keyboard connected to the Windows system.
Layer1: This layer will be activated when your keyboard's system toggle switch to Windows or Mac system and long press Fn1(3) key.
Layer2: This layer will be activated when your keyboard's system toggle switch to Windows or Mac and key mapped any key to MO(2), save and then long press it.

Layer3: This layer will be activated when your keyboard's system toggle switch to Windows or Mac, key mapped any key to MO(3), save and then long press it.
Keys Descriptions:
Table mapping keys to functions like Hue+, Sat+, RGB M+, RGB Tog., Win..., Mac..., Hue-, Sat-, BT 1, BT 2, BT 3, Brght+.

保修声明: 感谢您对我司产品的信任与支持, 为了您放心使用本产品, 更好地保障您的权益, 我们将严格遵守并执行相关规定...
产品保修信息:
Table with columns: Product Name, Warranty Period, Part Name, Warranty Period (Month), Warranty Service Type, Notes.

