



Ajazz K870T

Extended Manual



Table of Contents

Introduction	3
Comments by Epomaker	3
Warranty Information	3
Where To Buy	3
Unboxing	4
What's Included in the box	4
Keyboard Specifications	4
Keycap Dimensions	5
Key Combinations	5
Mac Keys	5
Windows Keys	6
System Switching	6
Backlight Settings	6
Extra Shortcuts	7
Quick Startup	8
Indicator Information	8
Charging Information	8
Bluetooth Preface	8
Wired Mode	8
Wireless Mode	8
Bluetooth Connection	9
Windows 10 Bluetooth	9
iOS Bluetooth Setup	11
MacOS Bluetooth	14
Backlight Creation	16
Create a Backlight Preset	16
Unofficial Software Support	17
Download Unofficial Software	17
Custom Backlight Options	18
Custom Layout Options	19
Custom Macro Creation	21

Introduction

Comments by Epomaker

If you think any part of this manual needs correction, adjustment or updating, send the team a message at support@epomaker.com . You can also send a message there if you have any issues with your keyboard.

Warranty Information

Epomaker's Warranty covers any factory defects that might affect the proper functionality of your purchase. It doesn't cover any damage that may occur from normal wear and tear. If your product is defective we will send you a replacement unit. Replacement units might require you to send the defective unit back to Epomaker.

We provide a 1 year warranty for our products when bought from our website (Epomaker.com). Your item will not be covered by your 1 year warranty if the inspection shows any sign of modification or changes unsupported by the original product, these include: Changing internal components, Assembling and reassembling the product, Replacing Batteries, etc.

We will ONLY cover the item if it is bought from our stores, you do not have a warranty with us if you bought the item from another reseller or likewise. You are required to contact them to resolve issues.

Where To Buy

Website

<http://epomaker.com/>

Amazon US

<https://www.amazon.com/s?me=A31XCF3C216O31&marketplaceID=ATVPDKIKX0DER>

Amazon UK

<https://www.amazon.co.uk/s?k=EPOMAKER>

Amazon DE


<https://www.amazon.de/s?k=EPOMAKER>

Aliexpress

<https://www.aliexpress.com/store/5877346>

Unboxing

What's Included in the box



1. Epomaker Ajazz K870T
2. Ten Rainbow Keycaps
3. USB-A to USB-C Cable (1.6m / 5.2ft)
4. Ajazz K870T Manual
5. Keycap Puller

Keyboard Specifications

Product Brand: Ajazz

Product Model: K870T

Battery Capacity: 2000mAh

Interface Type: USB-C

Bluetooth Capable: Yes

Wired Capable: Yes


Keyboard Dimensions: 362mm x 134mm x 34.5mm

Product Weight: 880g

Keyboard Layout: Tenkeyless, 87 Keys

Reprogrammable: No

Keycap Dimensions



The “units” of a keycap refer to a comparison between a one “unit” standard key. This is such that a 2u key will be two units of a 1u key.

Key Combinations

Mac Keys

F1	Decrease Screen Brightness
F2	Increase Screen Brightness
F3	Mission Control Access
F4	Main Control Panel
F7	Previous Song
F8	Play/Pause
F9	Next Song
F10	Mute
F11	Volume -
F12	Volume +

Windows Keys

FN + F5	Previous Song
FN + F7	Next Song
FN + F9	My Computer
FN + F10	Calculator
FN + F11	Homepage
Fn + F12	Search

System Switching

FN + S	Windows Mode
FN + A	Mac Mode

Backlight Settings

FN + INS	Always On/Single On/Single Off
FN + Home	Rainbow Options
FN + Page Up	Rain/Rainbow Rain/Slow Rain
FN + Del	Reactive Press
FN + End	Slow Strobe
FN + Page Down	Pulsating Waves
FN + 1	FPS Lights*
FN + 2	LOL Lights*
FN + 3	Office Lights*
FN + ~	Record/Save Lighting Mode
FN + Up Arrow	Light Brightness +
FN + Down Arrow	Light Brightness -
FN + Left Arrow	Light Direction

FN + Right Arrow	Backlight Color
FN + +	Light Speed +
FN + -	Light Speed -

* Lights Can Be Edited

Extra Shortcuts

FN + WIN	Lock Windows Key
FN + P	Bluetooth Pairing Mode
FN + Q/W/E	Bluetooth Device Switching

Quick Startup

Indicator Information

- **A** Caps Lock Indicator - Blue = On
-  Charging Indicator - Red = Charging
-  Connection Mode - Off = Wired, On = Bluetooth
-  Wheel Function - Off = Volume, Backlight Brightness = On

Charging Information

If the battery is low on the keyboard, the FN key will flash to indicate that the keyboard requires a charge. When the keyboard is charging, you should see the charging indicator, which will be red. When the keyboard is fully charged, this indicator will turn off.

Bluetooth Preface

Wired Mode

Disable the Connection mode to off. Connect the USB-A to USB-C cable. You will see the animation of the lights turning off indicating the keyboard is connected. You do not have to turn on the switch at the back of the keyboard to use wired.


Wireless Mode

Make sure the switch at the back is turned to "On" and the Connection Mode indicator is On, and should be a Blue color. The keyboard is then ready to be paired.

Bluetooth Connection

Windows 10 Bluetooth


1. First, charge the keyboard via a USB port on your computer until it has decent charge. You should see the Red light turn off on the indicator when it is full.
2. Make sure the switch at the back is turned to “On” and the Connection Mode indicator is On, and should be a Blue color. The keyboard is then ready to be paired.
3. First Press **FN + P**, It will flash a white colour indicating pairing mode.




4. Press the windows key, and type “Bluetooth” into the search.
5. Select “Bluetooth and other device settings”




6. Select "Add Bluetooth or other device"



7. Select "Bluetooth" from the add devices section. Make sure your "P" key is still flashing. If it stops flashing, it means your device will not be seen in the Bluetooth list and you will need to press it again so it can be paired to.




8. Select the “Key” From the device selection, it might also appear as “Ajazz K870T Keyboard”.
9. Assign the device to a key. You can assign up to three devices using **FN + Q**, **FN + W**, or **FN + E**.




Your device will then be paired on that specific button. To disconnect/reconnect the keyboard, press the same button until the button turns white.

iOS Bluetooth Setup


1. First, charge the keyboard via a USB port on your computer until it has decent charge. You should see the Red light turn off on the indicator when it is full. Make sure the switch at the back is turned to “On” and the Connection Mode indicator is On, and should be a Blue color. The keyboard is then ready to be paired.
2. First Press **FN + P**, It will flash a white colour indicating pairing mode.
3. Press the “Settings” Application from the home section on your iDevice.




4. Select “Bluetooth” from the Settings. Make sure it is on. Make sure that your device is considered discoverable.
5. Assign the device to a key. You can assign up to three devices using **FN + Q**, **FN + W**, or **FN + E**.



6. Press “AJAZZ K870T Keyboard” to connect to your Epomaker Ajazz K870T.




When your keyboard is connected to your iPhone, it should show as “Connected”. You should be able to type on it normally.




Note: If you want to disconnect the device, you can press the information icon on the side, and then select “Disconnect” or “Forget this device”. Your device will then be paired on that specific button. To disconnect/reconnect the keyboard, press the same button until the button turns white.

MacOS Bluetooth


Note: make sure your device is discoverable and turned on.



1. Press Command + Space to open Search
2. Type "Bluetooth" into the Spacebar, select "Bluetooth" (Don't select Bluetooth File Exchange).
3. First, charge the keyboard via a USB port on your computer until it has decent charge. You should see the Red light turn off on the indicator when it is full.
4. Make sure the switch at the back is turned to "On" and the Connection Mode indicator is On, and should be a Blue color. The keyboard is then ready to be paired.
5. First Press **FN + P**, It will flash a white colour indicating pairing mode.



6. You should see "Ajazz K870T Keyboard" in the Bluetooth devices. Assign the device to a key. You can assign up to three devices using **FN + Q**, **FN + W**, or **FN + E** when it connects to the device.
7. Press "Connect" to connect to the keyboard.



8. You should see a keyboard symbol that is connected. The mac keyboard assistant dialogue might pop up. Follow through the instructions and the keyboard should register input properly.

Backlight Creation

Create a Backlight Preset



We can assign different colours to the three presets on the lighting. We can change the lighting within **FN + 1**, **FN + 2**, and **FN + 3**.

1. Press the recording key by holding **FN + ~**. This will allow for you to assign lighting to different keys.
2. Press any key you would like lit up, and press it multiple times to change the colors, and you can press it a few times and it will turn the light off.
3. Press the key you want to save your custom backlighting to. You can place it in either **FN + 1**, **FN + 2**, or **FN + 3**.
4. You can then change the colours using **FN + Left Arrow** if you dislike the colors you picked and want a static color.

Unofficial Software Support


The software introduced by this chapter is not endorsed by Epomaker and should be used at your own risk. We will not be held liable for using this software and should only be used by advanced users. **DO NOT DOWNLOAD ANY FIRMWARE!**

We will not be providing any technical support for this software.


Download Unofficial Software

Download Link:


https://drive.google.com/file/d/1EHPGrqPKiIRgJYXHHFy_9UvXto29uQSG/



1. Download the file RAKK Lam-Ang Tuner
2. Extract the File using 7Zip (<https://www.7-zip.org/>) or Winrar.




3. Run through the installer until it installs the software. Make sure your keyboard is connected in wired mode or it will not detect the device.




4. Search for the “RAKK Lam-Ang” software and launch the application.

Custom Backlight Options



1. Head to the lighting section of the application



2. Select your preset, you can also make user defined ones, if your keyboard is connected, then you will see it change to your desired lighting. You can also select your colour, or "Full Color", which is Rainbow Mode.

Custom Layout Options



1. Go to the customize section, select one of the keys you would like to adjust




2. Select the keyboard option to reassign to a keyboard key. You can also use this to assign keys, combo keys, etc. Reminder, this is not official software. Some features might not work.




3. Assign the key you would like into the menu, and then click "Ok" to save it to your keyboard.


Custom Macro Creation



1. Head to the Macro section of the software, you should see the section which can be used to record and save the macros.



2. Enter the name you would like to use for the macro, and then press the "New" button.



3. Click "Start Record" and then begin typing, you will see on the right panel it will record your key presses.
4. When you are done, click "Stop Recording, and "Apply".